

Fire department access box ready for a padlock (not supplied). Your fire department will access this box which when opened, will cause the gate operator to open the gate. Contact your local fire department for instructions on which padlock to use. Most fire departments use knoxbox, but some may use different suppliers.

www.knoxbox.com/Products/Commercial-KnoxBoxes

Calimet Gate Operators

Use 14-20 gauge awg wire (not included) and splice (join) with the white and black wires.

Insert wires into green terminal normally located on the bottom right of the circuit board.

White wire → 24V-COM

Black wire → EXIT LOOP

Other Brand Gate Operators

Use 14-20 gauge awg wire (not included) and splice (join) with the white and black wires.

White wire → 24V Common

Black wire → Normal Open Relay